

FIST-SODF2

FIST small optical distribution frame

FIST is a Fiber Infrastructure System Technology.

FIST-SODF2 is a metal rack designed to serve as small optical distribution frame in an exchange, head end or customer premises environment.

The small ODF accommodates FIST modules that provide the functions of splicing and patching.

The unit has the following features

- Slim footprint: 300 mm wide, 300 mm deep
- Modular concept: basic rack that accepts up to 4 modules for the splicing and patching function
- Up to 144 fibers can be terminated to push-pull connectors having splices organized in a single circuit way. The capacity is limited to 96 terminations for other connector types.
- Cable attachment provision and patchcord management system included in the rack
- Cable entrance and patchcord outlet possible both in the top or both in the bottom of the rack
- Bend control on all fiber routing
- Transparent acrylic door



Dimensions and rack capacity

Description	Dimensions in mm			Capacity
	H	W	D	
FIST-SODF2	2200	300	300	4 modules

The rack is painted (powder coated) in light grey (RAL-7035).

Rack

FIST-SODF2 - 2 X

Rack height

2 2.2 m

Cable and patchcord entrance

B Bottom
T Top

Module

FIST-SODF2 - M - X XX - XX XX

Splice holder type

S For SMOUV splice protectors
A For ANT splice protectors

Module capacity

24 All connector types
36 Only possible for push-pull connector types

Connector adapter type

Standard connector type

Min.return loss	SC	FC	E2000	ST	None
45 dB (PC)				T0	NN
50 dB (UPC)	S1	F1			
60 dB (APC 8°)	S2	F2	E9		
60 dB (APC 9°)	S3*				

Low loss connector type

Min.return loss	SC	FC	E2000
50 dB (UPC)	S6	F6	
60 dB (APC 8°)	S7	F7	E8
60 dB (APC 9°)	S8*		

* In case of adapters only (no pigtails), select adapter reference S2 or S7.

Pigtails

NN No pigtails included
PT Pigtails included
PR Pigtails pre-installed

FIST, SMOUV, TE (logo) and TE Connectivity are trademarks of the TE Connectivity group of companies and its licensors.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

Tyco Electronics Raychem bvba

Diestsesteenweg 692

3010 Kessel-Lo, Belgium

Tel 32-16 351 011 (USA)1-919-557-8900

Fax 32-16 351 697 (USA)1-919-557-8498

www.te.com

www.telecomnetworks.com

TC 1029/DS/1 07/06

