



OCSH

Shelf for OCM5 optical component modules

The OCSH is a mechanical shelf assembly that accommodates OCM5 type of modules in a rack or cabinet environment.

The shelf is typically used in 19" active racks or data racks, but is also compatible with Tyco Electronics FIST racks and cabinets.

The OCSH-I unit has the following features:

- Can be front or back mounted in the rack
- Occupies 3 height units (19" standard)
- Allows the storage of 6 modules
- Front access to the modules
- Pigtails enter and leave the shelf via the left or right
- A cover including identification label is provided
- An optional repair facility for damaged pigtails is available.

The OCSH-L unit has the following features:

- Can be back mounted in the rack or cabinet
- Occupies 4 height units (19" standard)
- Allows the storage of up to 18 modules
- Front access to the modules
- Pigtails can enter the shelf at the left or right (when turned upside down).

Dimensions and ordering information

Description		Dimensions in mm			Capacity OCM5 Modules
		H	W	D	
OCSH-I-R	19" shelf (pigtailed leaving shelf at the right side)	125	481	280	6
OCSH-I-L	19" shelf (pigtailed leaving shelf at the left side)	125	481	280	6
OCSH-L-S	19" shelf	170	481 501 (incl. drums)	242	18

Accessories for OCSH-I

Ordering reference	Description
FIST-MB2-M	Mounting bracket for use in ETSI racks (1 pair)
FIST-MB2-B	Mounting bracket for use in 23" racks (1 pair)
OCSH-SPLICE-KIT	Repair facility for damaged pigtailed

Accessories for OCSH-L

Ordering reference	Description
FIST-MB-M	Mounting bracket adapters for use in ETSI racks (1 pair)
FIBRB-MB-B	Mounting bracket adapters for use in 23" racks (1 pair)

The shelf is painted (powder coated) in light grey (RAL 7035).

Tyco Electronics, TE logo and FIST are trademarks

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, Tyco Electronics makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. Tyco Electronics' obligations shall only be as set forth in Tyco Electronics' Standard Terms and Conditions of Sale for this product and in no case will Tyco Electronics be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of Tyco Electronics products should make their own evaluation to determine the suitability of each such product for the specific application.

Tyco Electronics Raychem NV
Diestsesteenweg 692
3010 Kessel-Lo, Belgium
Tel 32-16 351 011 (USA)1-919-557-8900
Fax 32-16 351 697 (USA)1-919-557-8498
www.tycoelectronics.com
www.telecomosp.com
TC 1022/DS/2 07/07



Tyco Electronics
Our commitment. Your advantage.